
Hardware Manual

Development Board DK50

Order No. 539361



© 2004 Beck IPC GmbH

Table of Contents

1. INTRODUCTION 3

1.1 GENERAL 3
1.2 ACCESSORIES 3
1.3 GETTING STARTED 3

2. FUNCTIONAL DESCRIPTION 4

2.1 BLOCK DIAGRAM 4
2.2 ELECTRICAL INTERFACE SPECIFICATION 6
2.2.1 Connector S1: COM interface 6
2.2.2 Connector S2: EXT interface 6
2.2.3 Pin header SL1: COM 7
2.2.4 Pin header SL2: EXT 7
2.2.5 Pin header SL3: SC13 / SC11 pin header 8
2.2.6 Pin header SL4: 8-bit input/output port 10
2.2.7 Pin header SL5: Hardware expansion port 11
2.2.8 Jumper Sx: Description 12
2.2.9 Push-button SW1: Reset 13
2.2.10 Push-button SW3: power fail 13
2.2.11 IC34 socket 13
2.2.12 LED description 13
2.2.13 Connector X1: Compact Flash Card 14
2.2.14 Connector X2: Ethernet 14
2.2.15 Connector X5: Power connector 14
2.3 MECHANICAL SPECIFICATIONS 15
2.4 ENVIRONMENTAL SPECIFICATIONS 15

3. APPLICATION NOTES 16

3.1 COMPACT FLASH COMPATIBILITY 16
3.2 EXPANSION EXAMPLE 16
3.3 DATA RETENTION IN THE EVENT OF AN UNEXPECTED POWER FAILURE 16
3.4 ALTERNATIVE POWER CONNECTOR 17

4. GENERAL CONDITIONS OF USE 18

4.1 SCOPE OF APPLICATION 18
4.2 EXCLUSION OF WARRANTY AND LIABILITY 18

5. LABELLING 19

6. SCHEMATICS 20

7. LIST OF REVISIONS 22

8. CONTACT 23


© 2004 Beck IPC GmbH

1. Introduction

1.1 General

The Development Board DK50 is an evaluation platform for the new IPC@CHIP Embedded Controller SC11 and SC13. This manual describes the hardware functionality of the DK50 Board.

The development board provides all the basic functions required to put the Embedded Controller SC11 and SC13 into operation, including a bread board area for customer-specific extensions. It provides, for example, a socket for the Embedded Controller, two serial ports, an Ethernet interface with traffic LED, eight digital I/O, Compact Flash socket and a switching DC/DC converter.



1.2 Accessories

The following accessories are not part of the delivery and can be ordered separately:

Order number:	Accessories:
536079	SC13 Embedded Web Controller
538428	SC11 Embedded Controller
195837	ZK14 serial programming cable
538934	PSE10 power supply for DK50

1.3 Getting Started


The functional start-up of the DK50 and software operations are described in the ‘Getting Started IPC@CHIP Embedded Web Controller’ document. You can download the document at:
http://www.beck-ipc.com/ipc/gettingstarted

© 2004 Beck IPC GmbH

2. Functional description

2.1 Block diagram

The electrical block diagram of the DK50 is shown in the following figure:




The DK50 provides:

- Socket for Embedded Controller SC11 or SC13
- Power supply with power fail detection
- Power LED
- Reset button
- Power fail button
- Serial port 0 (EXT)
- Serial port 1 (COM)
- Ethernet interface with traffic LED
- Compact Flash socket
- Eight digital outputs with status LEDs
- Eight digital inputs
- SC13 test connector
- Two free programmable LEDs

© 2004 Beck IPC GmbH

The location of the basic functions is shown in the following figure:



The standard jumper configuration is marked in blue.

2.2 Electrical interface specification

2.2.1 Connector S1: COM interface

Electrical specification: RS232-level

Default function: Terminal interface (STDIO), 19200 Baud, 8 data bits, no parity, 1 stop bit

Max. baud rate: 115Kbit/s

Pin assignment of the DSUB 9 male connector:

Pin	Name	Description
1	NC	not connected
2	RXD	receive data
3	TXD	transmit data
4	NC	not connected
5	GND	ground
6	NC	not connected
7	RTS	ready to send
8	CTS	clear to send
9	NC	not connected

2.2.2 Connector S2: EXT interface

Electrical specification: RS232-level

Default function: Serial RTOS update interface (BIOS update speed is 115k Baud). The EXT interface can also be used as a terminal interface (see also IPC@CHIP API documentation).


Max. baud rate: 115Kbit/s

Pin assignment of the DSUB 9 male connector:

Pin	Name	Description
1	NC	not connected
2	RXD	receive data
3	TXD	transmit data
4	NC	not connected
5	GND	ground
6	NC	not connected
7	RTS	ready to send
8	CTS	clear to send
9	NC	not connected

© 2004 Beck IPC GmbH

DSUB connector front view:



2.2.3 Pin header SL1: COM

The four jumpers connecting the pins 5-6 / 7-8 / 9-10 / 11-12 provide a serial RS232 interface on connector S1. Disabling this function provides 5V CMOS logic signals of a possible higher baud rate on pin 6, 8, 10, 12 or allows you to use the alternative SC13 / SC11 functions at these pins.

The standard COM function of the SC11/13 does not use the hardware handshake signals RTS and CTS. It is therefore possible to disable the RTS1 and CTS1 jumper and to use the pins 10, 12 with their alternative function.

Pin	Name	Description	
1	NC	not connected	
2	+5V	supply voltage output (the external load should not exceed 400mA)	
3	NC	not connected	
4	GND	ground	
5	RS232-TXD	transmit data, RS232 level	(default =closed)
6	TXD1	transmit data CMOS logic level	
7	RS232-RXD	receive data RS232 level	(default =closed)
8	RXD1	receive data, CMOS logic level	
9	RS232-CTS	clear to send, RS232 level	(default =closed)
10	CTS1	clear to send, CMOS logic level	
11	RS232-RTS	ready to send, RS232 level	(default =closed)
12	RTS1	ready to send, CMOS logic level	
13-16	NC	not connected	

2.2.4 Pin header SL2: EXT

The four jumpers connecting the pins 5, 6/7, 8/9, 10/11, 12 provide a serial RS232 interface on connector S2. Disabling this function provides 5V CMOS logic signals of a possible higher baud rate on pin 6, 8, 10, 12 or allows you to use the alternative SC13 / SC11 functions at these pins.

The standard EXT function of the SC11/13 doesn't use the hardware handshake signals RTS and CTS. It is therefore possible to disable the RTS1 and CTS1 jumper and to use the pins 10, 12 with their alternative function.

PIN	Name	Description
1	NC	not connected
2	+5V	supply voltage output (the external load should not exceed 400mA)

© 2004 Beck IPC GmbH

3	NC	not connected	
4	GND	ground	
5	RS232-TXD	transmit data, RS232 level	(default =closed)
6	TXD1	transmit data CMOS logic level	
7	RS232-RXD	receive data RS232 level	(default =closed)
8	RXD1	receive data, CMOS logic level	
9	RS232-CTS	clear to send, RS232 level	(default =closed)
10	CTS1	clear to send, CMOS logic level	
11	RS232-RTS	ready to send, RS232 level	(default =closed)
12	RTS1	ready to send, COMS logic level	
13-16	NC	not connected	

2.2.5 Pin header SL3: SC13 / SC11 pin header

The Embedded Controller pins are connected to this connector to enable hardware extensions or measurements.

Pin	Name	Description
1	PIO7 RXD0	Programmable I/O Pin Receive Data
2	PIO8 TXD0	Programmable I/O Pin Transmit Data
3	PIO9 CTS0	Programmable I/O Pin Clear To Send
4	PIO10 RTS0	Programmable I/O Pin Ready To Send
5	PIO11 TXD1	Programmable I/O Pin Transmit Data
6	PIO12 INT3 RXD1	Programmable I/O Pin Maskable Interrupt Receive Data
7	PIO13 INT0 TMROUT0	Programmable I/O Pin Maskable Interrupt Timer Output
8	AD0	Multiplexed address bus
9	AD1	
10	AD2	
11	AD3	
12	AD4	
13	AD5	
14	AD6	
15	AD7	
16	GND	GND
17	RESET# NMI Traffic_LED	Reset Non Maskable Interrupt Ethernet Traffic
18	TPTX+	Twisted Pair Driver
19	TPTX-	Twisted Pair Driver
20	TPRX+	Twisted Pair Receive
21	TPRX-	Twisted Pair Receive
22	RD#	Read Enable
23	WR#	Write Enable

© 2004 Beck IPC GmbH

24	ALE PCS0#	Address Latch Enable Peripheral Chip Selects
25	CTS1 PCS2# INT2 PWD INTA# PIO6	Clear To Send Peripheral Chip Selects Maskable Interrupt Pulse Width Demodulation Interrupt Acknowledge Programmable I/O Pin
26	RTS1 PCS3# INT4 PIO5	Ready To Send Peripheral Chip Selects Maskable Interrupt Programmable I/O Pin
27	A0 PCS1# TMRIN0 PIO4	Non Multiplexed Address Bus Peripheral Chip Selects Timer Input Programmable I/O Pin
28	A1 PCS5# TMRIN1 TMROUT1 PIO3	Non Multiplexed Address Bus Peripheral Chip Selects Timer Input Timer Output Programmable I/O Pin
29	A2 PCS6# PIO2	Non Multiplexed Address Bus Peripheral Chip Selects Programmable I/O Pin
30	DRQ0 INT5 PIO1	DMA Request Maskable Interrupt Programmable I/O Pin
31	DRQ1 INT6 PIO0	DMA Request Maskable Interrupt Programmable I/O Pin
32	VCC	+5V Power supply

For technical details about the Embedded Web Controller Family please download the IPC@CHIP Hardware Manual at: http://www.beck-ipc.com/ipc/download

© 2004 Beck IPC GmbH

2.2.6 Pin header SL4: 8-bit input/output port

This connector provides an 8-bit input and an 8-bit output port. The default port address 0x600 can be changed with the PCSx select jumper (S8..S12). The output port is equipped with status LEDs.

Output HIGH = LED lights up

Output LOW = LED dark

Each output pin can drive 5V / 20mA source, 40mA sink (do not drive more than 60mA at the whole port).

In their default state the outputs are connected with jumper to the inputs. The inputs and outputs can be used separately. In this case the jumpers have to be removed in order to avoid problems due to two different signal levels. The input and output pins are conform to TTL logic input and output logic level specifications.

Pin	Name	Description	Pin	Name	Description
1	I0	input bit 0	2	O0	output bit 0
3	I1	input bit 1	4	O1	output bit 1
5	I2	input bit 2	6	O2	output bit 2
7	I3	input bit 3	8	O3	output bit 3
9	I4	input bit 4	10	O4	output bit 4
11	I5	input bit 5	12	O5	output bit 5
13	I6	input bit 6	14	O6	output bit 6
15	I7	input bit 7	16	O7	output bit 7

I/O port examples to use this port from the command shell:

Switch on port bits 0..3, switch off port bits 4..7:

ALE 1 enables the ALE function

PCS 6 enable the PCS6 function

OB 600 0F write hex-byte 0F to I/O address 600 hex

Print input state of the I/O port:

ALE 1 enables the ALE function

PCS 6 enable the PCS6 function

IB 600 display the input state of the I/O address 600 hex

© 2004 Beck IPC GmbH

2.2.7 Pin header SL5: Hardware expansion port

This pin header can be also used for hardware expansions, with the provided signals and ready to connect I/O ports etc. to the DK50.

Pin	Name	Direction	Description
1	Vcc		+5V supply for the external load (should not exceed 400mA)
2	GND		ground
3	NC		not connected
4	NC		not connected
5	PIO1	I/O	SC13 / SC11 PIO pin, not buffered, with 10k Ohm pull up resistor for I2C functionality
6	D0	I/O	multiplexed address/data bus, bit 0
7	PIO0	I/O	SC13 / SC11 PIO pin, not buffered, with 10k Ohm pull up resistor for I2C functionality
8	D1	I/O	multiplexed address/data bus, bit 1
9	PIO13	I/O	SC13 / SC11 PIO pin, not buffered
10	D2	I/O	multiplexed address/data bus, bit 2
11	PIO3	I/O	SC13 / SC11 PIO pin, not buffered
12	D3	I/O	multiplexed address/data bus, bit 3
13	A0	O	latched address bus, bit 0
14	D4	I/O	multiplexed address/data bus, bit 4
15	A1	O	latched address bus, bit 1
16	D5	I/O	multiplexed address/data bus, bit 5
17	A2	O	latched address bus, bit 2
18	D6	I/O	multiplexed address/data bus, bit 6
19	A3	O	latched address bus, bit 3
20	D7	I/O	multiplexed address/data bus, bit 7
21	A4	O	latched address bus, bit 4
22	RD1#	O	buffered SC13 / SC11 RD# signal The data at the address/data bus (D0..7) is valid with the rising edge at this signal
23	A5	O	latched address bus, bit 5
24	WR1#	O	buffered SC13 / SC11 WR# signal The data at the address/data bus (D0..7) is valid with the rising edge at this signal
25	A6	O	latched address bus, bit 6
26	CSx40#	O	These signals (CS0x40#, CS0x50#, CS0x60# and CS0x70#) are four low active chip selects for external hardware expansions. They indicate sub-

© 2004 Beck IPC GmbH

			address areas of 16 bytes according to the selected PCSx signal (Jumper S8,S9,S10,S11 and S12). For example: Selected PCSx: PCS5# (Jumper S11) CS0x40# = address area 540hex ..54Fhex CS0x50# = address area 550hex ..54Fhex CS0x60# = address area 560hex ..56Fhex CS0x70# = address area 570hex ..57Fhex With a low signal, the system indicates to the external hardware an I/O operation at the specified address area.
27	A7	O	latched address bus, bit 7
28	CSx50#	O	see also pin 26
29	NC		not connected
30	CSx60#	O	see also pin 26
31	NC		not connected
32	CSx70#	O	see also pin 26
33	NC		not connected
34	RES#	O	Reset from the reset button and Power on reset. Low active. Min. pulse width = 100ms.

2.2.8 Jumper Sx: Description

S5: GND both pins are ground points for measurement

S6: PIO 3 (default = closed) opening this jumper disables the PIO3 LED

S7: PIO13 (default = closed) opening this jumper disables the PIO13 LED

S8, S9, S10, S11, S12: PCSx select

PCSx selection of a 256 byte I/O area. The selection influences the used addresses for the Compact Flash X1, the SL4 I/Os. On the expansion port SL5 the data bus and the four chip selects CSx40#, CSx50#, CSx60#, and CSx70# are influenced by this setting.

Default for x = PCS6#, which is the setting for the base address 0x600. Possible further selections are PCS5#, PCS3#, PCS2# or PCS1#,

Note: Due to the multifunctional pins of the IPC@CHIP, the CTS1 jumper from the SL1 connector must be disabled if PCS2# is used and the jumper from RTS1 if PCS3# is used.

S13: Power-Fail-Detection Enable/Disable

default = closed/enabled

© 2004 Beck IPC GmbH

If the Jumper is closed, the power fail circuitry will detect an under-voltage below 16V at the external power supply input and will cause an NMI at the SC13 / SC11 RESET#/NMI/TRAFFIC pin. As soon the NMI procedure is started within the SC13 / SC11 the supply voltage must be brought to a voltage of at least 19V to restart the SC13 / SC11.
Removing the jumper will disable the under-voltage detection. The power fail button can still be used. This is helpful when using the DK50 with a supply voltage below 16V.

2.2.9 Push-button SW1: Reset

Resets the SC13 / SC11, the Compact Flash Card and the 8-bit port. This reset function can also be used at the expansion port (SL5) at pin 34 RES#.

2.2.10 Push-button SW3: power fail

This push-button simulates a power fail by forcing a NMI at the SC13 / SC11.

2.2.11 IC34 socket

This is the socket for the SC13 / SC11. The small dot at the corner of the SC13 / SC11 represents the pin 1.

2.2.12 LED description

Power LED
Displays the supply voltage (+5V) state.

Traffic LED
This LED is for visual monitoring of the Ethernet. The LED dims according to the traffic on the Ethernet.
Please note: This is not a link-status LED. The LED remains dark, when the Ethernet is connected to the DK50 and there is no traffic on the Ethernet.

PIO3 LED
Free programmable PIO3 LED can be accessed at the command line with the PIO command:
PIO 3 4 switch LED at PIO3 off
PIO 3 5 switch LED at PIO3 on
Use the PIO command without parameters to display the state of all PIO pins.

PIO13 LED
Free programmable PIO13 LED can be accessed at the command line with the PIO command
PIO 13 4 switch LED at PIO13 on
PIO 13 5 switch LED at PIO13 off
Use the PIO command without parameters to display the state of all PIO pins.

Compact Flash LED
Compact Flash Card activity LED.

© 2004 Beck IPC GmbH

2.2.13 Connector X1: Compact Flash Card

Compact Flash Card socket.

This Compact Flash Card interface provides an 8-bit True IDE Mode.

For the Compact Flash Cards Type I according to the Compact Flash Specification Rev 2.0 published by the Compact Flash Association.

2.2.14 Connector X2: Ethernet

Ethernet connector 100/10 BaseT LAN interface

The Ethernet is not usable together with the SC11 Embedded Controller.


Pin assignment of the RJ45 connector:

Pin	Name	Description
1	TX+	transmit data, differential
2	TX-	transmit data, differential
3	RX+	receive data, differential
4		
5		
6	RX-	receive data, differential
7		
8		

2.2.15 Connector X5: Power connector

Supply voltage: 24V DC (12V .. 30V)

Power consumption: 3.5 watts max. including the SC13 / SC11 and Compact Flash Card



© 2004 Beck IPC GmbH

2.3 Mechanical specifications

Length:	167 mm
Width:	100 mm
Height:	17 mm
Weight:	110 g (without Embedded Controller)

2.4 Environmental specifications

Temperature:

Non-operating (storage):	-25°C to 70°C (EN60068-2-1/2)
Operating:	0°C to 55°C (EN 60068-2-1/2)
Changes:	EN 60068-2-14

Electrical:

DC Input voltage:	24 V typical (12...30V), max. ripple 250mVp-p
Power dissipation:	3.5 W max. without extensions
DC Input current:	500 mA / 5V typical without extensions
Max load on +5V:	400 mA for customer specific extensions
Logic Inputs:	TTL; 0 to +5 V

Approbation:

None

© 2004 Beck IPC GmbH

3. Application notes

3.1 Compact Flash compatibility

The Development Board DK50 has been tested with CF cards from Sandisk, Toshiba and Lexar. Compatibility problems have been reported with some CF cards from Kingston and Extrememory. For the use of the Compact Flash Card the EXTIDE.EXE driver must be started already on the SC13 / SC11. The EXTIDE.EXE driver can be downloaded at:


http://www.beck-ipc.com/ipc/download/extide

The reason for the problems with some CF cards are over- and undershoots on the signal lines because of the fast switching signal drivers combined with the layout design.

In the redesigned DK50 D1-2 H02 serial resistors reducing this over and undershoots at the signal lines to the CF (IORD#, IOWR, A0, A1 and A2). For details please refer to the DK50 D1-2 schematic.

Please note: For designs similar to the DK50 these 5 resistor values have to be adapted, because the signal quality depends on the printed circuit board track length and routing.

3.2 Expansion example



The circuitry shows an easy expansion example with the DK50 development board.


3.3 Data retention in the event of an unexpected power failure

The Power Fail circuit will trigger an NMI in the SC13 / SC11 if the operating voltage falls below 16VDC. This enables the processor to interrupt the running program in order to save important data quickly or to close any files that are still open on the Compact Flash card. In order that the processor has sufficient time for these tasks, an additional capacitor on the 24VDC side is required to store sufficient energy. This capacitor must be added to the DK50 board (i.e. on bread board area).

© 2004 Beck IPC GmbH

Typically 50ms are required to close only open files on the Compact Flash card, and additionally 100ms are required to write 2Kbyte of non-volatile data to the SC13 / SC11.

We recommend adding a 3300µF/35V aluminum electrolytic capacitor per 100ms for data retention in case of unexpected power failure.
The figure shows the connection of an external capacitor to the DK50 board (capacitor plus pole on the cathode of diode ZD2):



3.4 Alternative power connector

Connector X4 is vacant for an alternative power supply connector. The X4 connector pins are connected to the X5 power supply connector pins.

PIN	Name	Description
1	+24V	Supply Voltage (+12..30V)
2	GND	GND

4. General conditions of use

4.1 Scope of application

Use of the DK51 Development Kit is permissible exclusively under the conditions stated below. These conditions of use shall be deemed as accepted with the commissioning of the Development Kit.


4.2 Exclusion of warranty and liability

This product is a development system without CE mark. The system must therefore only be used for hardware/software development. Use of the Development Kit outside the specified environment is the responsibility of the user and shall be carried out at his or her own risk, exempting Beck from any liability.
Claims by the user for compensation against Beck in conjunction with the use of this product shall be excluded.


Insofar that information, hardware, software and documentation is transferred without charge, liability is excluded for any material defects and deficiencies in title of the information, hardware, software and documentation, in particular for their correctness or absence of faults, completeness and/or usability.


© 2004 Beck IPC GmbH

5. Labelling


3M - N7E50-X615XX-20
Compact Flash Connector
X1
X3
Vcc (+5V)
GND
SL5
SL4
Port 0x600 IN
Port 0x600 OUT
LED 0x600 OUT
CF-LED LD78
BECK IPC GmbH
www.beck-ipc.com
DK50 H01
Expansion port
SW3
power fail
SW1
reset
IC34
SC13 socket
SL3
Pin1 (DOT)
LED PIO13 LD76
LD77 LED PIO3
S6 PIO3
S7 PIO13
PCSX select
S12 PCS6#
S11 PCS5#
S10 PCS3#
S9 PCS2#
S8 PCS1#
S5 GND
SL2
SL1
traffic LED LD79
NMI disable S13
+24V
GND
X2
Ethernet
S2
EXT
S1
COM
X5
LD48 power LED
24V supply voltage

6. Schematics




DK50D1-2 H02
SPE
Rev 1.2
(c) 2004
Document Number
Size B
Sheet 2 of 2
Date: Thursday, February 09, 2006
BECK IPC GmbH
Germany - 35415 Pohlheim
Grüninger Weg 24
THE POINT OF SYNERGY
AD[0..7]
A[0..7]
D[0..7]
ALE
RD#
WR#
RES#
PCSx#
IC20 ABT245
IC21 ABT573
IC22 ABT138
IC23B
IC23C
IC23D ABT32
U7A ABT32
IC24 74ABT273
IC26 74ABT541
SL5 Expansion
SL4
X1 CompactFlashConnector
LD78 LED Flash active
D68 D69 D70 D71 D72 D73 D74 D75
R60 R61 R62 R63 R64 R65 R66 R67 680R
R57 1k
R78 10k
R89 10k
R90 10k
R104 470R
R105 470R
R107 220R
R108 220R
R109 220R
C55 100n
C85 4u7
C61 C62 C63 C64 C65 C66 100n
JUMPER S8 S9 S10 S11 S12
VCC
GND

7. List of revisions

Rev.	Comments
1.2	Initial revision
1.3	address update
1.4	DK50 redesign (DK50 D1-2 H02): serial resistors in CF signals
1.5	schematic update

© 2004 Beck IPC GmbH

8. Contact

BECK IPC GmbH
Grüninger Weg 24
D-35415 Pohlheim
Germany
Phone: +49 (0)6404-695-0
Fax: +49 (0)6404-695-205
Internet: www.beck-ipc.com
E-Mail: info@beck-ipc.com

©2004 BECK IPC GmbH All rights reserved. No part of this document may be copied or reproduced in any form or by any means without the prior written consent of BECK IPC GmbH. The information in this document is subject to change without notice. Devices sold by BECK IPC GmbH are covered by warranty and patent indemnification provisions appearing in BECK IPC GmbH Terms and Conditions of Sale only.

BECK IPC GmbH MAKES NO WARRANTY, EXPRESS, STATUTORY, IMPLIED OR BY DESCRIPTION, REGARDING THE INFORMATION SET FORTH HEREIN OR REGARDING THE FREEDOM OF THE DESCRIBED DEVICES FROM INTELLECTUAL PROPERTY INFRINGEMENT. BECK IPC GmbH MAKES NO WARRANTY OF MERCHANTABILITY OR FITNESS FOR ANY PURPOSE.

BECK IPC GmbH shall not be responsible for any errors that may appear in this document. BECK IPC GmbH makes no commitment to update or keep current the information contained in this document.

Life critical applications - BECK products are not authorised for use as critical components in life support devices or systems unless a specific written agreement pertaining to such intended use is executed between the customer and BECK prior to use. Life support devices or systems are those which are intended for surgical implantation into the body, or which sustain life, and whose failure to perform, when properly used in accordance with instructions for use provided in the labelling, can be reasonably expected to result in significant injury to the user. BECK IPC GmbH customers using or selling these products for use in such applications do so at their own risk and agree to fully indemnify BECK IPC GmbH for any damages resulting from such application.

Right to make changes - Beck IPC GmbH reserves the right to make changes without notice in the products, including software, described or contained herein in order to improve design and/or performance. Beck IPC GmbH assumes no responsibility or liability for the use of any of these products.